



# Power generator **FH 6001 R**

Nr art. 28156

## Characteristic

- Voltage stabilization  $\pm 1\%$
- Low level of THD  $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP IP 23
- Full single phase power output socket 32 Amps

## Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>6,2 kW</b>
<b>Nominal power</b>	<b>5,6 kW</b>
<b>Prime current</b>	<b>24,3 A</b>
Engine	Honda
Model	GX 390
Capacity	389 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	6,1 L
Consumption (load 75%)	2,7 L / h
Noise level Lwa	97 dB(A)
Weight	69 kg
Length	790 mm
Width	580 mm
Height	505 mm

## Standard equipment

- AVR
- Socket 230 V 16 A
- Socket 230 V 32 A
- Overload protection
- Oil level sensor

## Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10118
- Hourmeter Nr art. 23300
- Transportation set Nr art. 28807
- Service kit (air filter, spark plug, engine oil) Nr art. 16582

## Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/WE**  
Low Voltage Directive
- **2014/30/WE**  
EC Directive